

LogiLink®

Notebook Power Adapter 45W

Art. No.: PA0170



Ideal as a replacement or secondary power adapter for various notebooks at home and in the office.

Features:

- » 45W Universal Notebook Power Adapter with 9 changeable tips
- » Charge most brands of laptops in market with multiple easy-to-install tips
- » Reliable replacement or secondary power adapter in home or office
- » Full safety design: Built-in protection against over current, over voltage, over temperature and short-circuit protection.



Home/Office

For Acer/Asus/Dell/HP/Lenovo/LG/MSI/Samsung/Sony/Toshiba laptop

Power Tips Compatible Table:

K3	6.5 x 4.4 mm	Sony 19.5V 2A
K4	5.5 x 3.0 mm	Samsung 19V 2.1A
K5	5.5 x 2.5 mm	Asus/Toshiba/Lenovo/LG/MSI 19V 1.58A/2.37A, 20V 2A
K6	5.5 x 1.7 mm	Acer 19V 1.58A/2.1A
K9	4.5 x 3.0 mm	Dell 19.5V 2.31A
K10	4.5 x 3.0 mm	HP 19.5V 2.31A
K13	3.0 x 1.0 mm	Samsung/Asus 19V 2.1A/2.37A
K14	2.5 x 0.7 mm	Asus 19V 1.58A/2.1A
K18	4.0 x 1.2 mm	Asus 19V 1.75A/2.37A



PA0170



Made in China



RoHS
compliant



* The specifications and pictures are subject to change without notice.
* All trade names referenced are the registered namework of their respective owners.

Best Connectivity

LogiLink®


Notebook Power Adapter 45W

Art. No.: PA0170



Specification:

Input Voltage	AC 100-240V 50/60Hz 1.1A max
Output Power	19-20V 1.58-2.37A 45W max
Efficiency	Level VI
Dimension	57 x 57 x 29mm (not including cable)
Weight	178g
Cable Length	1.8m



Package Contents:

- » 1 x Power Adapter for Notebook
- » 9 x Changeable Tips
- » 1 x User Manual

Package Informations:

- » Packing Dimension: 194 x 127.5 x 42mm
- » Packing Weight: 0.3kg
- » Carton Dimension: 450 x 268 x 205mm
- » Carton Q'ty: 20pcs
- » Carton Weight: 7.4kg

Warning

- *For use with Information Technology Equipment.
- *Compare the specifications of your device with the specifications of the adapter. The power current (A) of your device should be equal to or lower than the power current of the power supply.
- *Only to be used indoor.
- *Only to be used after powering on.
- *Only to be used within max load.
- *Remove the power adapter from its power source after use.



PA0170



Made in China



RoHS
compliant



* The specifications and pictures are subject to change without notice.
*All trade names referenced are the registered namework of their respective owners.